

1                   **CIRCUIT BREAKER FOR A DUAL-CIRCUIT**

2    BACKGROUND OF THE INVENTION

3    1. Field of the Invention

4           The present invention is related to a circuit breaker to automatically  
5    terminate an electricity supply in an excessive-demand condition, and more  
6    particularly to a circuit breaker with four terminals used for a dual-circuit.

7    2. Description of Related Art

8           For protecting electrical equipment, a circuit breaker is generally used to  
9    terminate a supply of electricity when a device connected to the supply starts to  
10   draw an excessive amount of electricity.

11          A conventional circuit breaker is generally provided with two terminals.  
12   A bimetallic strip with a movable node is formed on one of the terminals. In a  
13   normal state, the movable node is electrically connected with an immovable  
14   node formed on the other terminal. In an excessive-demand condition, the  
15   bimetallic strip becomes hot and deforms whereby the movable node is  
16   disconnected from the immovable node to switch off the circuit.

17          However, the conventional circuit breaker can only be used in a single-  
18   circuit closed by the two terminals, and cannot be used in a dual-circuit which  
19   needs four terminals to close it.

20          Therefore, the invention provides a circuit breaker for a dual-circuit to  
21   mitigate and/or obviate the aforementioned problems.

22   SUMMARY OF THE INVENTION

23          The main objective of the present invention is to provide a circuit  
24   breaker which has four terminals to terminate a dual-circuit in an excessive-

1 demand condition.

2 Other objectives, advantages and novel features of the invention will  
3 become more apparent from the following detailed description when taken in  
4 conjunction with the accompanying drawings.

#### 5 BRIEF DESCRIPTION OF THE DRAWINGS

6 Fig. 1 is a perspective view of a circuit breaker with four terminals in  
7 accordance with the invention;

8 Fig. 2 is an exploded perspective view of the circuit breaker in Fig. 1;

9 Fig. 3 is a cross sectional front view of the circuit breaker in a  
10 switched-off state;

11 Fig. 4 is a cross sectional front view of the circuit breaker in a  
12 switched-on state;

13 Fig. 5 is a cross sectional back view of Fig. 3;

14 Fig. 6 is a cross sectional side view of the circuit breaker along the line  
15 "6-6" in Fig. 4; and

16 Fig. 7 is a partial perspective view of the circuit breaker.

#### 17 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

18 With reference to Figs. 1-3, a circuit breaker for a dual-circuit in  
19 accordance with the invention has a body (10) and two chambers (11, 12)  
20 separately defined in the body (10). The first chamber (11) has a first terminal  
21 (110) and a second terminal (111) mounted therein and extending out from a  
22 lower side of the body (10). The first terminal (110) has a first immovable node  
23 (13) formed at an upper end thereof, and the second terminal (111) has a  
24 bimetallic strip (14) extending above the first terminal (110). A first movable

1 node (15) is formed at a distal end of the bimetallic strip (111) and aligned with  
2 the first immovable node (13). When the first movable node (15) is electrically  
3 connected with the first immovable node (13), the first circuit (primary circuit)  
4 of the dual-circuit is closed.

5         The second chamber (12) has a third terminal (120) and a fourth terminal  
6 (121) mounted therein and extending out from the lower side of the body (10).  
7 The third terminal (120) has a second immovable node (16) formed at an upper  
8 end thereof, and the fourth terminal (121) has a metal strip (17) extending above  
9 the third terminal (120). A second movable node (18) is formed at a distal end of  
10 the metal strip (17) and aligned with the second immovable node (16). A linkage  
11 (19) transversally extends between the metal strip (17) and the bimetallic strip  
12 (14) and has a first end (not numbered) mounted at a middle portion of the metal  
13 strip (17) and a second end (not numbered) abutting on the bimetallic strip (14).  
14 When the second movable node (18) is electrically connected with the second  
15 immovable node (16), the second circuit (secondary circuit) of the dual-circuit is  
16 closed.

17         A reset button (20) is pivotally mounted at an upper side of the body (10).  
18 A tab (21) is formed at a bottom side of the reset button (20) and located in the  
19 first chamber (11) and near the first movable node (15). A hook (30) installed on  
20 the tab (21) is attached to the distal end of the bimetallic strip (14), as shown in  
21 Fig. 3. When the reset button (20) is pressed to pull upwards the bimetallic strip  
22 (14) by the hook (30), the first movable node (15) is disconnected from the first  
23 immovable node (13). At the same time, the linkage (19) is pushed upward by  
24 the bimetallic strip (14) to disconnect the second movable node (18) from the

1 second immovable node (16), as shown in Figs. 5 and 6. In this case, the linkage  
2 (19) has a slight deformation with an elastic force.

3 With reference to Fig. 4, when the reset button (20) is pressed to close  
4 the dual-circuit, the tab (21) pushes the bimetallic strip (14) downwards to  
5 connect the first movable node (15) with the first immovable node (13). Under  
6 the elastic force of the linkage (19), the metal strip (17) is also moved  
7 downwards to connect the second movable node (18) with the second  
8 immovable node (16). Then, the dual-circuit is closed.

9 When the circuit undergoes an excessive-consumption of electricity, the  
10 bimetallic strip (14) becomes hot and deforms upwards to disconnect the first  
11 movable node (15) from the first immovable node (13), as shown in Fig. 3. At  
12 the same time, the linkage (19) is pushed upward by the bimetallic strip (14) to  
13 disconnect the second movable node (18) from the second immovable node (16),  
14 as shown in Figs. 5 and 6). Then, the dual-circuit is terminated.

15 Furthermore, with reference to Figs. 2 and 7, if the bimetallic strip (14)  
16 deforms to excessively raise the second end of the linkage (17) abutting on the  
17 bimetallic strip (14), the first end of the linkage (17) on the metal strip (17) may  
18 be pressed down and the metal strip (17) cannot be pulled upward to terminate  
19 the second circuit. Therefore, a stop (41) is formed on a side wall (40) of the first  
20 chamber (11) and protruded above the bimetallic strip (14). After the bimetallic  
21 strip (14) deforms upwards to disconnect the first movable node (15) from the  
22 first immovable node (13), the second end of the linkage (17) abutting on the  
23 bimetallic strip (14) is blocked by the stop (41) and will not be excessively raised,  
24 and the first end of the linkage (17) can be moved upwards to disconnect the

1 second movable node (18) from the second immovable node (16).

2 According to the present invention, the circuit breaker for the dual-  
3 circuit is provided with the bimetallic strip to terminate the primary circuit, and  
4 the metal strip connected by the linkage to terminate the secondary circuit. The  
5 cost of the metal strip is lower than the bimetallic strip, so the circuit breaker has  
6 a low cost and a high security.

7 It is to be understood, however, that even though numerous  
8 characteristics and advantages of the present invention have been set forth in the  
9 foregoing description, together with details of the structure and function of the  
10 invention, the disclosure is illustrative only, and changes may be made in detail,  
11 especially in matters of shape, size, and arrangement of parts within the  
12 principles of the invention to the full extent indicated by the broad general  
13 meaning of the terms in which the appended claims are expressed.